

INDUSTRIAL SERIES

1022P

PRIME PO	WER	STAND-BY I	POWER
kVA	kW	kVA	kW
1022	818	1125	900

3~ 50 Hz. 400V	•
PERKINS	*
EU STAGE 0	\$2
70 dB(A) @ 7 mt	4 0
400 lt	J

ENVIRONMENTAL CONDITIONS	
Temperature	40° C
Height	1000 mslm
Humidity	60%

OPEN VERSION B1700

SOUNDPROOF VERSION C1400



WEIGHT	DIM	ENSIONS	
kg	L [mm]	W [mm]	H [mm]
8125	5000	2100	2600



The image is only for demonstration purposes

WEIGHT	DIN	1ENSIONS	
kg	L [mm]	W [mm]	H [mm]
9760	6680	2200	3250





	TECHNICAL L	DETAILS	
ELECTRICAL DATA	Electrical system type	3F+N	~
	Power factor	0,8	φ
	Voltage	400	V
	Frequency	50	Hz
	PRP Ampere rating	1475	А
	Engine	PERKINS 4008-TAG2A	
	Engine emissions standard (REG. UE 2016/1628)	EU STAGE 0	
	RPM governor	Electronic	
	Performance class (ISO8528-5)	G2	
	Rpm	1500	rpm
NE NE	Nr. of cylinders	8	
ENGINE	Bore x stroke	160 x 190	mm
	Displacement	30561	сс
	Induction system	Turbocharged	
	Cooling system	Water	
	Engine net prime power	1154 (861)	Hp (kW)
	Exhaust gas aftertreatment	/	
z	Fuel type	Diesel	
CONSUMPTION	Consumption @ 50-75-100% carico – load - charge	111 – 162 – 215	lt/h
NSUN	Standard tank capacity	400	lt
8	Autonomy @ 75% carico – load - charge	2,5	h
	Alternator	STAMFORD – MECC ALTE – MARELLI MOTORI	
	Туре	Self excited, brushless	
OR	Number of poles	4	
ALTERNATOR	Insulation class	н	
ALTE	Temperature rise class	н	
	Voltage regulation	AVR	
	Voltage precision	± 0,5	%
	Sound level (soundproof version)	70	dB(A) 7mt
GENERAL	Exhaust pipe diameter	300	mm
	Electrical system voltage	24	V



ELECTRIC PANEL

MANUAL

AUTOMATIC MAINS FAILURE



Electronic control unit with multimeter	COMAP AMF25	COMAP AMF25
Electrical panel enclosure protection degree	IP	44
ON-OFF electric panel switch	Key type	Without key
Emergency pushbutton	STANDARD	
Battery charge maintainer	/	24V 10A
Power supply	Full power terminal	Full power terminal
Circuit breaker	Magnetothermal type 4P ABB Tmax-T 1600A	Magnetothermal type 4P ABB Tmax-T 1600A
Main protection alarms	Min-max V and Hz. LOP. HWT. Battery o	harger alternator failure. Low fuel level

STANDARD ELECTRONIC CONTROL UNIT

COMAP AMF25



Functions: automatic or manual start, remote start, periodic test

Multimeter V (L1, L2, L3, N), A (L1, L2, L3), Hz, kVA, battery V, hour counter

Backlit LCD display. USB port

 $Communication\ accessories\ available:\ Ethernet,\ GSM-GPRS,\ 4G,\ GPS$

MODBUS and SNMP communication protocols support

Advanced PLC configurability

OPTIONAL ELECTRONIC CONTROL UNIT





SOUNDPROOF AND WEATHERPROOF CANOPY



Self-supporting frame material	Galvanized carbon steel sheets, electro-welded, minimum thickness 6 mm	
Soundproof canopy material	Galvanized carbon steel sheet, electro-welded, thickness between 2 and 9 mm	
Painting	Epoxy powder RAL5015 textured, outdoor-proof	
In-built fuel tank	400 lt + Drip tray	
Soundproofing coating material	Polyester fiber. Fire resistance EN13501-1 class B	
	On the top of the canopy. Residential type with sound reduction 35 dB(A)	
Access openings	n.4 doors with padlockable key lock	
Electric panel	Lateral side position. Dedicated door with padlockable key lock	
Fresh air intake and hot air expulsion	₹ \$	
Lifting system	n.4 lifting hooks	
Support feet	n.6 support feet with holes for machine ground fastening	



MAIN OPTIONS



1600A automatic transfer switch (ATS)



1050 It bigger fuel tank with drip tray



2000W engine preheating system with integrated circulating pump



Automatic fuel transfer kit with manual by-pass system

Residual current protection relay adjustable in sensitivity and intervention time

OTHER OPTIONS

Power distribution socket set
Synchronizing electric panel
Battery switch
Remote control systems ETHERNET, 2G - 3G - 4G, GPS

Further alternator brand

Quick couplings for connecting an external tank with three way valve

Outdoor, underground and transportable tanks

Slow or fast towing trailer

Front hot air expulsion canopy

Further colors

Greenpower AB

Helsingborgsvägen Varalöv, 262 96 Ängelholm, Sweden

Phone: +46 43122240

Email: info@greenpower.se Web: www.greenpower.se